

POWERI – generating sets powered by HONDA – petrol engine

TYPE NO	E3200	POWERI 5001 H	POWERI 4/7503 H	POWERI 6501 H	POWERI 7503 H	POWERI 7/10 H	POWERI 12,5 H-S
Rating VA	2 500	5 000	7 500	6 500	7 500	10 000	12 500
Contin. Rating W	2 000	3 900	3 900	5 800	6 000	6 400	10 000
Protection frame	yes	yes	yes	yes	yes	yes	yes
ENGINE	GX 160	GX 270	GX 270	GX 390	GX 390	GX 390	GX 620
Nominal hp	5,5	9	9	13	13	13	20/14,9
Rating hp/3000 rpm	3	6	6	10,3	10,3	10,3	16,2
Displacement cc	163	270	270	389	389	389	614
Oil guard	yes	yes	yes	yes	yes	yes	yes
Fuel tank litres	3,6	6	6	6,5	6,5	6,5	20
Consumt. max l/h	0,5-1,1	0,7-1,8	0,7-1,8	1,2-2,9	1,2-3,2	1,2-3,2	1,6-4,6
Noise dB	66	71	71	76	76	76	87
Cooling	air	air	air	air	air	air	air
GENERATOR	S15W	S16W	T16F	S16F	T16F	T20FS	T20FS
Rating VA	2 500	5 000	7 500	6 500	7 500	10 000	12 500
Voltage V	230	230	230/400	230	230/400	230/400	230/400
Circuit breaker A	10	16	4 x 10	20	4 x 10	4 x 16	4 x 16
Resid.cur.device	-	-	yes	-	yes	yes	yes
Socket 230 V	2 pcs	2 pcs	2 pcs	2 pcs	2 pcs	2 pcs	2 pcs
Socket 400 V	-	-	1 pc	-	1 pc	1 pc	1 pc
Warranty years	1	1	1	1	1	1	1
Dimens. l-w-h cm	63-46-42	70-50-50	70-50-50	70-50-50	70-50-50	70-50-50	96-53-50
Weight kg	38	54	73	73	79	92	105

Optionals:

- Electric start
- Wheelsets
- Extra fuel tanks
- V-, A-, Hz- ja H-meters
- Remote control
- Loadstarting
- Automatic mains failure control system
- Weather / noise protection



E3200



POWERI 7/10 H